HCI+2

2-Foot Rail Extension

For Use with HCI-12 12-foot "I-beam" Rail


Installation Instructions

4. REMOVE SPROCKET



USA & Canada (800) 421-1587 & (800) 392-0123 (760) 438-7000 - Toll Free FAX (800) 468-1340 www.linearcorp.com

AFTER THE CHAIN IS LOOSENED. REMOVE THE SPROCKET HOLDER FROM THE END OF THE RAIL



1. PRODUCT DESCRIPTION

5. REMOVE RAIL BOLT

The Model HCI+2 2-foot "I-rail" extension is designed to be compatible with the Model HCI-12 12-foot chain-drive "I-rail" used in commercial garage door installations and in carriage house garage door installations. The 2-foot extension, when added to the 12-foot "I-rail", provides a 14-foot long rail for operating high-lift doors.

The kit includes two "T-rail" sections that bolt together to form an "I-rail" and connect to the main "I-rail" using two reinforcing straps. The kit also includes two short lengths of chain to extend the stock chain.

IMPORTANT NOTE:


Linear's pre-assembled chain-drive rails are now being produced configured for quieter operation with the trolley traveler located next to the turnbuckle on the chain (turnbuckle adjacent). Earlier chain rails have the trolley traveler located on one side of the rail, and the turnbuckle located on the other side of the rail (turnbuckle opposite). This extension kit will work for both types of rail configurations.


When using this extension with the turnbuckle adjacent rails, connect the two short lengths of extension chain supplied together to form one longer chain, and attach that chain to the non-traveler side of the turnbuckle. See Steps 15 & 16.


When using this extension kit with the *older rails*, attach a short extension chain to each side of the turnbuckle. See Steps 15 & 16.

BOTTOM RAIL SECTION REINFORCING STRAPS (2) TOP BAIL SECTION \$\rightarrow\$ \$\rightarrow\$ 1/4-20 KEPS NUTS (5)


2. KIT CONTENTS TURNBUCKLE ADJACENT RAIL HAS TRAVELER NEXT TO HOLD SCREWDRIVER IN TURNBUCKLE TURNBUCKLE SLOT NOTE: ONE SIDE OF THE TURNBUCKLE IS LEFT-HAND THREAD. THE OTHER SIDE IS RIGHT-HAND THREAD FOR EITHER RAIL TYPE. UNSCREW AND REMOVE EACH END FROM THE TURNBUCKLE LOOSEN THE TWO TURNBUCKLE LOCKING NUTS TURNBUCKLE OPPOSITE RAIL HAS TRAVELER ON ONE SIDE AND TURNBUCKLE **EXTENSION CHAINS (2)** ON THE OTHER SIDE












10. ALIGN TOP EXTENSION RAIL BETWEEN STRAPS

6. IDENTIFY TOP AND BOTTOM EXTENSION RAILS



11. INSTALL REMAINING TWO STRAP BOLTS

7. ALIGN REINFORCING STRAPS

3. LOOSEN AND DISASSEMBLE TURNBUCKLE

